# **SWITCHMODE™ Power Rectifier**

These state-of-the-art devices use the Schottky Barrier principle with a proprietary barrier metal.

#### **Features**

- Dual Diode Construction, May be Paralleled for Higher Current Output
- Guard-Ring for Stress Protection
- Low Forward Voltage Drop
- 125°C Operating Junction Temperature
- Maximum Die Size
- Short Heat Sink Tab Manufactured Not Sheared!
- Pb-Free Package is Available

#### **Mechanical Characteristics**

- Case: Epoxy, Molded, Epoxy Meets UL 94 V-0
- Weight: 1.7 Grams (Approximately)
- Finish: All External Surfaces Corrosion Resistant and Terminal Leads are Readily Solderable
- Lead and Mounting Surface Temperature for Soldering Purposes: 260°C Max. for 10 Seconds
- Device Meets MSL1 Requirements
- ESD Ratings: Machine Model, C (>400 V) Human Body Model, 3B (>8000 V)

#### **MAXIMUM RATINGS**

Rating	Symbol	Value	Unit
Peak Repetitive Reverse Voltage Working Peak Reverse Voltage DC Blocking Voltage	V <sub>RRM</sub> V <sub>RWM</sub> V <sub>R</sub>	30	V
Average Rectified Forward Current (At Rated V <sub>R</sub> , T <sub>C</sub> = 115°C) Per Device	lo	15 30	Α
Peak Repetitive Forward Current (At Rated $V_R$ , Square Wave, 20 kHz, $T_C = 115^{\circ}C$ )	I <sub>FRM</sub>	30	Α
Non-Repetitive Peak Surge Current (Surge Applied at Rated Load Conditions Halfwave, Single Phase, 60 Hz)	I <sub>FSM</sub>	300	Α
Peak Repetitive Reverse Surge Current (1.0 μs, 1.0 kHz)	I <sub>RRM</sub>	2.0	Α
Storage Temperature Range	T <sub>stg</sub>	-55 to +150	°C
Operating Junction Temperature Range	$T_J$	-55 to +125	°C
Voltage Rate of Change (Rated V <sub>R</sub> , T <sub>J</sub> = 25°C)	dV/dt	10,000	V/μs
Reverse Energy, Unclamped Inductive Surge (T <sub>J</sub> = 25°C, L = 3.0 mH)	E <sub>AS</sub>	224.5	mJ


Maximum ratings are those values beyond which device damage can occur. Maximum ratings applied to the device are individual stress limit values (not normal operating conditions) and are not valid simultaneously. If these limits are exceeded, device functional operation is not implied, damage may occur and reliability may be affected.




### ON Semiconductor®

http://onsemi.com

## SCHOTTKY BARRIER RECTIFIER 30 AMPERES, 30 VOLTS





D<sup>2</sup>PAK CASE 418B PLASTIC

#### **MARKING DIAGRAM**



A = Assembly Location

Y = Year

WW = Work Week

B3030CTL = Device Code

G = Pb-Free Package

AKA = Diode Polarity

#### ORDERING INFORMATION

Device	Package	Shipping
MBRB3030CTL	D <sup>2</sup> PAK	50 Units / Rail
MBRB3030CTLG	D <sup>2</sup> PAK (Pb-Free)	50 Units / Rail


THERMAL CHARACTERISTICS (All device data is "Per Leg" except where noted.)

Characteristic	Symbol	Value	Unit
Thermal Resistance, Junction-to-Ambient (Note 1)	$R_{\theta JA}$	50	°C/W
Thermal Resistance, Junction-to-Case	$R_{\theta JC}$	1.0	°C/W

### **ELECTRICAL CHARACTERISTICS**

Maximum Instantaneous Forward Voltage (Note 2) (I <sub>F</sub> = 15 A, T <sub>J</sub> = 25°C) (I <sub>F</sub> = 30 A, T <sub>J</sub> = 25°C)	V <sub>F</sub>	0.44 0.51	V
Maximum Instantaneous Reverse Current (Note 2)	I <sub>R</sub>	0.01	mA
(Rated $V_R$ , $T_J = 25$ °C) (Rated $V_R$ , $T_J = 125$ °C)		2.0 195	


- 1. Mounted using minimum recommended pad size on FR-4 board.
- 2. Pulse Test: Pulse Width = 250  $\mu$ s, Duty Cycle  $\leq$  2.0%.



100 T<sub>J</sub> = 125°C T


Figure 1. Typical Forward Voltage

Figure 2. Maximum Forward Voltage



**Figure 3. Typical Reverse Current** 


**Figure 4. Maximum Reverse Current** 



10 P<sub>FO</sub>, AVERAGE POWER DISSIPATION (WATTS) 9.0 dc **SQUARE**  $lpk/lo = \pi$  -8.0 WAVE 7.0 lpk/lo = 5.06.0 5.0 lpk/lo = 104.0 lpk/lo = 20 3.0  $T_J = 125^{\circ}C$ 2.0 1.0 10 15 20 25 I<sub>O</sub>, AVERAGE FORWARD CURRENT (AMPS)

Figure 5. Current Derating

Figure 6. Forward Power Dissipation






Figure 7. Typical Capacitance

Figure 8. Typical Unclamped Inductive Surge




Figure 9. Typical Thermal Response

## **Modeling Reverse Energy Characteristics** of Power Rectifiers

Prepared by: David Shumate & Larry Walker ON Semiconductor Products Sector

#### **ABSTRACT**

Power semiconductor rectifiers are used in a variety of applications where the reverse energy requirements often vary dramatically based on the operating conditions of the application circuit. A characterization method was devised using the Unclamped Inductive Surge (UIS) test technique. By testing at only a few different operating conditions (i.e. different inductor sizes) a safe operating range can be established for a device. A relationship between peak avalanche current and inductor discharge time was established. Using this relationship and circuit parameters, the part applicability can be determined. This technique offers a power supply designer the total operating conditions for a device as opposed to the present single—data—point approach.

#### INTRODUCTION

In today's modern power supplies, converters and other switching circuitry, large voltage spikes due to parasitic inductance can propagate throughout the circuit, resulting in catastrophic device failures. Concurrent with this, in an effort to provide low–loss power rectifiers, i.e., devices with lower forward voltage drops, Schottky technology is being

applied to devices used in this switching power circuitry. This technology lends itself to lower reverse breakdown voltages. This combination of high voltage spikes and low reverse breakdown voltage devices can lead to reverse energy destruction of power rectifiers in their applications. This phenomena, however, is not limited to just Schottky technology.

In order to meet the challenges of these situations, power semiconductor manufacturers attempt to characterize their devices with respect to reverse energy robustness. The typical reverse energy specification, if provided at all, is usually given as energy—to—failure (mJ) with a particular inductor specified for the UIS test circuit. Sometimes the peak reverse test current is also specified. Practically all reverse energy characterizations are performed using the UIS test circuit shown in Figure 10. Typical UIS voltage and current waveforms are shown in Figure 11.

In order to provide the designer with a more extensive characterization than the above mentioned one-point approach, a more comprehensive method for characterizing these devices was developed. A designer can use the given information to determine the appropriateness and safe operating area (SOA) of the selected device.




Figure 10. Simplified UIS Test Circuit

#### **Suggested Method of Characterization**




Figure 11. Typical Voltage and Current UIS Waveforms

Utilizing the UIS test circuit in Figure 10, devices are tested to failure using inductors ranging in value from 0.01 to 159 mH. The reverse voltage and current waveforms are acquired to determine the exact energy seen by the device and the inductive current decay time. At least 4 distinct inductors and 5 to 10 devices per inductor are used to generate the characteristic current versus time relationship. This relationship when coupled with the application circuit conditions, defines the SOA of the device uniquely for this application.

#### **Example Application**

The device used for this example was an MBR3035CT, which is a 30 A (15 A per side) forward current, 35 V reverse breakdown voltage rectifier. All parts were tested to destruction at 25°C. The inductors used for the characterization were 10, 3.0, 1.0 and 0.3 mH. The data recorded from the testing were peak reverse current (Ip), peak reverse breakdown voltage (BVR), maximum withstand energy, inductance and inductor discharge time (see Table 1). A plot of the Peak Reverse Current versus Time at device destruction, as shown in Figure 12, was generated. The area under the curve is the region of lower reverse energy or lower stress on the device. This area is known as the safe operating area or SOA.




Figure 12. Peak Reverse Current versus
Time for DUT

Table 1. UIS Test Data

PART NO.	I <sub>P</sub> (A)	B <sub>VR</sub> (V)	ENERGY (mJ)	L (mH)	TIME (μs)
1	46.6	65.2	998.3	1	715
2	41.7	63.4	870.2	1	657
3	46.0	66.0	1038.9	1	697
4	42.7	64.8	904.2	1	659
5	44.9	64.8	997.3	1	693
6	44.1	64.1	865.0	1	687
7	26.5	63.1	1022.6	3	1261
8	26.4	62.8	1024.9	3	1262
9	24.4	62.2	872.0	3	1178
10	27.6	62.9	1091.0	3	1316
11	27.7	63.2	1102.4	3	1314
12	17.9	62.6	1428.6	10	2851
13	18.9	62.1	1547.4	10	3038
14	18.8	60.7	1521.1	10	3092
15	19.0	62.6	1566.2	10	3037
16	74.2	69.1	768.4	0.3	322
17	77.3	69.6	815.4	0.3	333
18	75.2	68.9	791.7	0.3	328
19	77.3	69.6	842.6	0.3	333
20	73.8	69.1	752.4	0.3	321
21	75.6	69.2	823.2	0.3	328
22	74.7	68.6	747.5	0.3	327
23	78.4	70.3	834.0	0.3	335
24	70.5	66.6	678.4	0.3	317
25	78.3	69.4	817.3	0.3	339

The procedure to determine if a rectifier is appropriate, from a reverse energy standpoint, to be used in the application circuit is as follows:

- a. Obtain "Peak Reverse Current versus Time" curve from data book.
- b. Determine steady state operating voltage (OV) of circuit.
- Determine parasitic inductance (L) of circuit section of interest.
- d. Obtain rated breakdown voltage (BVR) of rectifier from data book.
- e. From the following relationships,

$$V = L \cdot \frac{d}{dt}i(t)$$
  $I = \frac{(BVR - OV) \cdot t}{L}$ 

a "designer" l versus t curve is plotted alongside the device characteristic plot.

f. The point where the two curves intersect is the current level where the devices will start to fail. A peak inductor current below this intersection should be chosen for safe operating. As an example, the values were chosen as  $L=200~\mu H, \ OV=12~V$  and BVR=35~V.

Figure 13 illustrates the example. Note the UIS characterization curve, the parasitic inductor current curve and the safe operating region as indicated.




Figure 13. DUT Peak Reverse and Circuit Parasitic Inductance Current versus Time

#### SUMMARY


Traditionally, power rectifier users have been supplied with single–data–point reverse–energy characteristics by the supplier's device data sheet; however, as has been shown here and in previous work, the reverse withstand energy can vary significantly depending on the application. What was done in this work was to create a characterization scheme by which the designer can overlay or map their particular requirements onto the part capability and determine quite accurately if the chosen device is applicable. This characterization technique is very robust due to its statistical approach, and with proper guardbanding (6σ) can be used to give worst–case device performance for the entire product line. A "typical" characteristic curve is probably the most applicable for designers allowing them to design in their own margins.

#### References

- Borras, R., Aliosi, P., Shumate, D., 1993, "Avalanche Capability of Today's Power Semiconductors, "Proceedings, European Power Electronic Conference," 1993, Brighton, England
- Pshaenich, A., 1985, "Characterizing Overvoltage Transient Suppressors," <u>Powerconversion</u> <u>International, June/July</u>


#### **PACKAGE DIMENSIONS**

#### D<sup>2</sup>PAK CASE 418B-04 ISSUE J




- NOTES:
  1. DIMENSIONING AND TOLERANCING PER ANSI Y14.5M, 1982.
  2. CONTROLLING DIMENSION: INCH.
  3. 418B-01 THRU 418B-03 OBSOLETE, NEW STANDARD 418B-04.

	INCHES		MILLIM	IETERS
DIM	MIN	MAX	MIN	MAX
Α	0.340	0.380	8.64	9.65
В	0.380	0.405	9.65	10.29
С	0.160	0.190	4.06	4.83
D	0.020	0.035	0.51	0.89
E	0.045	0.055	1.14	1.40
F	0.310	0.350	7.87	8.89
G	0.100 BSC		2.54 BSC	
Н	0.080	0.110	2.03	2.79
J	0.018	0.025	0.46	0.64
K	0.090	0.110	2.29	2.79
L	0.052	0.072	1.32	1.83
M	0.280	0.320	7.11	8.13
N	0.197	REF 5.00 REF		REF
Р	0.079	0.079 REF		REF
R	0.039	REF	0.99 REF	
S	0.575	0.625	14.60	15.88
٧	0.045	0.055	1.14	1.40



#### **SOLDERING FOOTPRINT\***



\*For additional information on our Pb–Free strategy and soldering details, please download the ON Semiconductor Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

SWITCHMODE is a trademark of Semiconductor Components Industries, LLC.

ON Semiconductor and una are registered trademarks of Semiconductor Components Industries, LLC (SCILLC). SCILLC reserves the right to make changes without further notice to any products herein. SCILLC makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does SCILLC assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in SCILLC data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. SCILLC does not convey any license under its patent rights nor the rights of others. SCILLC products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the SCILLC product could create a situation where personal injury or death may occur. Should Buyer purchase or use SCILLC products for any such unintended or unauthorized application, Buyer shall indemnify and hold SCILLC and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that SCILLC was negligent regarding the design or manufacture of the part. SCILLC is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

#### **PUBLICATION ORDERING INFORMATION**

#### LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor P.O. Box 61312, Phoenix, Arizona 85082-1312 USA Phone: 480-829-7710 or 800-344-3860 Toll Free USA/Canada Japan: ON Semiconductor, Japan Customer Focus Center Fax: 480-829-7709 or 800-344-3867 Toll Free USA/Canada Email: orderlit@onsemi.com

N. American Technical Support: 800-282-9855 Toll Free

2-9-1 Kamimeguro, Meguro-ku, Tokyo, Japan 153-0051 Phone: 81-3-5773-3850

ON Semiconductor Website: http://onsemi.com

Order Literature: http://www.onsemi.com/litorder

For additional information, please contact your local Sales Representative.